

Table de Conversion Watts/dBm

$$(dBm)=10 \log P (mW)$$

$$P \text{ mW} = \text{antilog } dBm/10$$

Micro Watts	dBm	Micro Watts	dBm	Milli Watts	dBm	Milli Watts	dBm	Watts	dBm
1	-30	100	-10	1	0	100	20	1	30
2	-26.99	125	-9.03	2	3.01	125	20.97	2	33.01
3	-25.23	150	-8.24	3	4.77	150	21.76	3	34.77
4	-23.98	175	-7.57	4	6.02	175	22.43	4	36.02
5	-23.01	200	-6.99	5	6.99	200	23.01	5	36.99
6	-22.22	225	-6.48	6	7.78	225	23.52	6	37.78
7	-21.55	250	-6.02	7	8.45	250	23.98	7	38.45
8	-20.97	275	-5.61	8	9.03	275	24.39	8	39.03
9	-20.46	300	-5.23	9	9.54	300	24.87	9	39.54
10	-20	325	-4.88	10	10	325	25.12	10	40
15	-18.24	350	-4.56	15	11.76	350	25.44	15	41.76
20	-16.99	375	-4.26	20	13.01	375	25.74	20	43.01
25	-16.02	400	-3.98	25	13.98	400	26.02	25	43.98
30	-15.23	425	-3.72	30	14.77	425	26.28	30	44.77
35	-14.56	450	-3.47	35	15.44	450	26.53	35	45.44
40	-13.98	475	-3.23	40	16.02	475	26.77	40	46.02
45	-13.47	500	-3.01	45	16.53	500	26.99	45	46.53
50	-13.01	525	-2.8	50	16.99	525	27.2	50	46.99
55	-12.6	550	-2.6	55	17.4	550	27.4	55	47.4
60	-12.22	600	-2.22	60	17.78	600	27.78	60	47.78
65	-11.87	650	-1.87	65	18.13	650	28.13	65	48.13
70	-11.55	700	-1.55	70	18.45	700	28.45	70	48.45
75	-11.25	750	-1.25	75	18.75	750	28.75	75	48.75
80	-10.97	800	-0.97	80	19.03	800	29.03	80	49.03
85	-10.71	850	-0.71	85	19.29	850	29.29	85	49.29
90	-10.46	900	-0.46	90	19.54	900	29.54	90	49.54
95	-10.22	950	-0.22	95	19.78	950	29.78	95	49.78
100	-10	1000	0	100	20	1000	30	100	50

A afficher dans votre Labo!